

© By earphone hearing.

SENSITIVITY ADJUSTMENT

Turn the Sensitivity Tuner to - (minus) side to decreases the sensitivity and the detecting distance will be shorter. Turn the Sensitivity Tuner to + (plus) side to increases the sensitivity and the detecting distance will be longer.

INTERFERENCE (BACKGROUND NOISE) ELIMINATION

1. The Sensitivity tuner is also used to eliminate the background noise (interference).
2. If the scan environment has other noises that interfere with your detector, the strength indication LED will be lit up.
3. If this condition appears, adjust the sensitivity by turning the Sensitivity Tuner to - (minus) side to decreases the sensitivity until the Level 1 Yellow LED slightly lights up.
4. In normal condition, when turn on the power, only the Power LED (Green) lights up to confirm the detector is in normal condition.

LOW BATTERY WARNING

If your detector is turned on, and the bottom LED (Red) lights up without blinking, it means the batteries run down. Please replace new batteries.

FEATURES

1. Detecting frequency from 50 MHz ~ 3 GHz covering all kinds of hidden meras, cellular phones and Bugs, etc.
2. Fuzzy technique of multi-channel scanning.
3. Audio and light warning indicate the strength of detected signals.
4. Three kinds of detecting method for selection: Sound, Silent or Earphone hearing, fit to use anytime, anywhere.
5. Advanced sensitivity tuner for background noise elimination and distance adjustment.

NOTICE OF USE

1. If you are not going to use this device for a long time, remove the batteries to avoid damage caused by corrosion from battery leakage.
2. Unauthorized repair or disassembly of this device will void all the warranties.
3. Avoid water.
4. Do not store this device in an excessively hot place.
5. Avoid knocks or dropping this device.

SPECIFICATION

Power	AAA/UM-4 battery x 2, 3V DC
Detecting frequencies	50 MHz - 3.0 GHz
Dimension	L 87 x W 55 x H 24mm
Weight	90g
Warning mode 1	Audible alarm and 3 LEDs
Warning mode 2	Silent, only 3 LEDs (SH-055S) Vibration and 3 LEDs (SH-055SV)
Warning mode 3	Silent, 3 LEDs and earphone hearing
Detecting Distance 2.4GHz Wireless camera Cellular phone	about 5 feet (regular 10mW camera) about 20 feet

* Specification may change without notice.